
PCSM

IEC

Easy maintenance.
Integrated MV solution in the same enclosure.
Advanced grid support.
Compatible with all battery technologies.



Freemaq PCSM
IEC



Preliminary

REFERENCES		FP5381MH
AC	AC Output Power @40°C [1]	5380 kVA / kW
	AC Output Power @50°C [1]	4910 kVA / kW
	Operating Grid Voltage	33 kV ±10%
	Operating Grid Frequency	50 Hz
	Current Harmonic Distortion (THDi)	< 3% per IEEE 519
	Power Factor (CosPhi) [2]	0.5 leading ... 0.5 lagging
	Overload Capability	166% - 100 ms / 150% - 5 s / 120% - 8 s / 110% - 15 s
DC	DC Voltage Range [3]	1019 V – 1500 V
	Maximum DC Voltage	1500 V
	DC Voltage Ripple	< 3%
	Max. DC Continuous Current	5583 A
	Max. DC Short Circuit Current	500 kA with a time constant of 1 ms
	Battery Technology	All types of batteries (BMS required)
EFFICIENCY & AUX. SUPPLY	Efficiency (Max) (η)	98.00% including MV transformer
	Euroeta (η)	97.53% including MV transformer
CABINET	Dimensions [WxDxH]	23.5 x 6.5 x 7.2 ft
	Dimensions [WxDxH]	7.15 x 2.0 x 2.2 m
	Weight	32628 lbs
	Weight	14800 kg
	Type of Ventilation	Forced air cooling
ENVIRONMENT	Degree of Protection	IP55
	Operating Temperature Range	From -40 °C to +60 °C, >40 °C power derating (optional below -25 °C)
	Operating Relative Humidity Range	From 4% to 100%
	Storage Temperature Range	From -40 °C to +60 °C
	Max. Altitude (above sea level)	1000 m
CONTROL	Communication Protocol	Modbus TCP
	Power Plant Controller	Optional
	Keyed ON/OFF Switch	Standard
PROTECTIONS	Ground Fault Protection	Insulation monitoring device
	Humidity Control	Active heating
	General AC Protection & Disconnection	36 kV MV switchgear (2L+V)
	General DC Protection & Disconnection	High-speed fuses, Motorized DC disconnect switches [4]
	Overvoltage Protection	Type II for AC and Type I+II for DC
STANDARDS	Safety	IEC 62109-1 / IEC 62109-2 / IEC 62477-1 / IEC 62477-2
	Utility Interconnect [5]	IEC 62116 / G99 / VDE 4110-4120-4130 / CEI 0-16 / NTS 2.1 / EN 50549

NOTES

[1] Values at 1.00·Vac nom and CosPhi=1. Consult Power Electronics for derating curves.
[2] Consult P-Q charts available: $Q(kVAr)=\sqrt{(S(kVA)^2-P(kW)^2)}$.
[3] Consult Power Electronics for derating curves. In the event of overvoltage in the grid, the minimum DC voltage will vary proportionally with the AC voltage.
[4] Battery short circuit disconnection must be done on the battery side.
[5] Consult Power Electronics for other applicable standards / grid codes.

The content of this document is periodically updated. Power Electronics reserves the right to modify all or part of this document without prior notice.

V. 3.0.0 20261109

POWER ELECTRONICS