
Multi PCSM

UL

Easy maintenance.
Integrated MV solution in the same enclosure.
Up to 4 independent DC inputs.
Advanced grid support.
Compatible with all battery technologies.



Freemaq Multi PCSM
UL



Preliminary

REFERENCES		FP5230MU2	FP5230MU4
AC	AC Output Power @40°C [1]	5230 kVA / kW	
	AC Output Power @50°C [1]	4790 kVA / kW	
	Operating Grid Voltage	34.5 kV ±10%	
	Operating Grid Frequency	60 Hz	
	Current Harmonic Distortion (THDi)	< 3% per IEEE 519	
	Power Factor (CosPhi) [2]	0.5 leading ... 0.5 lagging	
	Overload Capability	166% - 100 ms / 150% - 5 s / 120% - 8 s / 110% - 15 s	
DC	DC Voltage Range [3]	976 V – 1500 V	
	Maximum DC Voltage	1500 V	
	DC Voltage Ripple	< 3%	
	Max. DC Continuous Current	2734 A	1367 A
	Max. DC Short Circuit Current	500 kA with a time constant of 1 ms	
	Battery Technology	All types of batteries (BMS required)	
	Number of Separated DC Inputs	2	4
EFFICIENCY & AUX. SUPPLY	Efficiency (Max) (η)	98.02% including MV transformer	
	CEC (η)	97.75% including MV transformer	
CABINET	Dimensions [WxDxH]	23.5 x 6.5 x 7.2 ft	
	Dimensions [WxDxH]	7.15 x 2.0 x 2.2 m	
	Weight	32628 lbs	
	Weight	14800 kg	
	Type of Ventilation	Forced air cooling	
ENVIRONMENT	Degree of Protection	NEMA 3R	
	Operating Temperature Range [4]	From -25 °C to +60 °C, >40 °C power derating	
	Operating Relative Humidity Range	From 4% to 100%	
	Storage Temperature Range	From -40 °C to +60 °C	
	Max. Altitude (above sea level)	2000 m	
CONTROL	Communication Protocol	Modbus TCP	
	Power Plant Controller	Optional	
	Keyed ON/OFF Switch	Standard	
PROTECTIONS	Ground Fault Protection	Insulation monitoring device	
	Humidity Control	Active heating	
	General AC Protection & Disconnection	38 kV MV Switchgear (V)	
	General DC Protection & Disconnection	High-speed fuses, Motorized DC disconnect switches [5]	
	Overvoltage Protection	Type II for AC and Type I+II for DC	
STANDARDS	Safety	UL 1741 / CSA 22.2 No.107.1-16	
	Installation	NEC 2023	
	Utility Interconnect [6]	UL 1741 SA & SB / IEEE 1547.1 / IEEE 2800	

NOTES

[1] Values at 1.00·Vac nom and CosPhi=1. Consult Power Electronics for derating curves.
[2] Consult P-Q charts available: Q(kVAr)=√(S(kVA)2-P(kW)2).
[3] Consult Power Electronics for derating curves. In the event of overvoltage in the grid, the minimum DC voltage will vary proportionally with the AC voltage.
[4] Optional for temperatures below -25 °C.
[5] Battery short circuit disconnection must be done on the battery side.
[6] Consult Power Electronics for other applicable standards / grid codes.

The content of this document is periodically updated. Power Electronics reserves the right to modify all or part of this document without prior notice.

V. 3.0.0 20261109

POWER ELECTRONICS